

The Multipath-IP T4000 Lite features the same highly advanced feature set as the original T4000 only in a smaller form factor and packing more inputs and outputs.

The on-board battery charger and PSTN dial through functions are not fitted to the T4000 Lite. With a smaller price tag, it is a great solution for installations where the T4000 Lite is being powered from an existing battery-backed alarm system. Its tiny footprint allows it to easily retrofit into existing alarm system cabinets.

Simply connect any Contact-ID enabled dialler panel into the 'Panel' port for instant cellular alarm reporting.

Along with all the features you have come to expect from T4000, such as Dual 4G and Ethernet alarm transmission paths, the Lite also brings modern capabilities to existing alarm systems such as smartphone apps and push notification service.\*

The three outputs built into the Lite are fully controllable from the SkyCommand app by the end user. The outputs can be programmed to control areas on the end user's alarm panel using a keyswitch input or used for general purpose remote control.

Using its industry first "Router Functionality", the T4000 Lite can even leverage Inner Range's SkyTunnel cloud-based infrastructure for seamless IP connectivity of Inner Range alarm systems.\*\*

The T4000 Lite also provides a communications path for upload/download programming of many popular alarm systems on the market when a PSTN line is not available at the installation site.



## Package Contents

- T4000 Lite Security Communicator
- 3.5 dBi Magnetic Base Antenna 2 meter cable
- Accessory Kit
- Installation Manual
- SIM Cards included

**998535**  
T4000 Lite Security Communicator,  
Dual SIM - Telstra/Optus

**998535NZ**  
T4000 Lite Security Communicator,  
Dual SIM - Vodafone NZ/  
Spark NZ



## Features

- Simple plug and play installation
- 4G Dual SIM
- Compatible with most alarm systems
- 3 inputs
- 3 outputs
- Over-the-air upload/download to compatible alarm systems
- Contact-ID and IRFast with text formats
- Remote Control using the SkyCommand smart phone app
- Minimal power consumption
- Over-the-air firmware updatable

## Specifications

### Physical

Size:	101(L) x 79(W) x 23(D) (mm) (Not including connectors)
Shipping Weight:	195g
Enclosure Type:	ABS plastic
Installation Environment:	0°C - 50°C @15% - 90% relative humidity (non-condensing)

### LED Indicators

Status Indicators:	5
--------------------	---

### Alarm Communications

Alarm Formats:	Contact ID, IRFast, IRFast + Text
----------------	-----------------------------------

### PABX

Max PABX line Voltage:	65V RMS
Max PABX Current:	30mA
PABX Output Level:	-10dBm
Max RF Power:	2 watts

\* Push notification subscription required.

\*\* Router data subscription required.

### Power Specifications

Input:	12-24VDC, 150mA Nominal
Current consumption @ 13V DC:	115mA (Idle) + 30mA (GSM Online)
Minimum operating voltage:	8V DC
Low volts sense voltage (typical):	11.0V
Fuse:	PTC protection + on-board fuse (non-replaceable)
Zone input:	3 Software configurable (EOL or Non-EOL)
Open Collector output (OUT) current:	3 100mA DC per output

### Compliance

Electrical:	
Environmental:	<b>RoHS</b> 